RAS-REM Series Remote Control Panel

RAS-REM-8 for RAS-208 Eight (8) Channel Stereo Audio Switcher RAS-REM-16 for RAS-216 Sixteen (16) Channel Monaural Audio Switcher





RAS-REM-8 Remote Control Panel for RAS-208 Eight (8) Channel Stereo Passive Audio Switcher front panel



RAS-REM-16 Remote Control Panel for RAS-216 Sixteen (16) Channel Monaural Passive Audio Switcher front panel

Features

- Remote Control Panel provides direct control of RAS-200 Series Passive Audio Switchers.
- Remote panels are identical to the look and feel of the front panel of each model.
- Long-distance RS-485 serial connection up to 1000 feet (305 meters). (25-foot (8-meter) CAT5 cable supplied with each unit.
- Simple connection with single CAT5 shielded cable.

The RAS-REM Remote Control Panel is an interface panel that is identical in look and function to the front panel of the RAS-208 or RAS-216 Passive Audio Switcher available from BDI. The RAS-REM remote control panels provide a short- or long-distance RS45 serial connection of up to 1000 feet (305 meters). The RAS-REM uses standard CAT5 shielded cable for interconnection. Each unit includes a 25-foot (8-meter) cable as standard.

Technical Specifications	RAS-REM-8	RAS-REM-16
Number of Controls:	Eight (8) Pushbuttons	Sixteen (16) Pushbuttons
Rear Panel Interface:	RJ45 for RS45 Serial Interface	
Interface Cable Limit:	CAT5 Shielded Cable up to 1000 feet (305 meters) in length	
Operating Ambient Temperature:	32 to 122 deg, F (0 to 50 deg, C)	
Humidity:	95%, Non-condensing	
Mechanical Dimensions:	19 in W x 2.25 in D x 1.75 in H (483 mm W x 57 mm D x 44 mm H) Standard One EIA Rack Unit Enclosure	
Shipping Information:	22 in W x 4 in D x 4 in H (559 mm W x 102 mm D x 102 mm H) 2 lbs (1 kg)	

